

Quickstart Casambi (flex10, flex10L, flex10X)

DE

1. „Casambi“ App auf mobiles Endgerät laden.
2. Ein Netzwerk erstellen
 - a. Netzwerke benötigen einen Namen (z.B. Büro 1) und können passwortgeschützt werden.
 - b. Um ein Netzwerk-Passwort zu schützen, ist ein Internetzugang notwendig. Außerdem muss eine E-Mail Adresse und jeweils ein Benutzer und ein Administrator - Passwort vergeben werden.
3. Profil ändern/auswählen in der App.
Notwendiger Vorgang vor dem hinzufügen in ein Netzwerk.

| <u>Abkürzung</u> | <u>Beschreibung</u> |
|---|--|
| BC | Broadcast (alle Geräte gemeinsam) |
| A0,A1,A2,... | DALI-Einzeladresse (=einzelne Geräte) |
| G0,G1,G2, ... | DALI-Gruppenadresse (= Gruppe von Geräten) |
| Empfohlenes Profil für Standard-DALI-Leuchten (DT6) | bDW (1pB – DALI/BC/Dim) |
| Empfohlenes Profil für Tunable-White-Leuchten(DT8) | bDW (1pB - DT8/BC/Dim,TW) |

Vorgehensweise um ein Profil zu ändern :

- Unten rechts auf „Mehr“ klicken.
- Anschließend auf „Geräte in der Nähe“ klicken (Alle verfügbaren Module sind hier gelistet).
- Modul wählen und auf „Profil ändern“ klicken.
- Passendes Profil auswählen. (Empfehlung siehe Tabelle)
- Update starten.

Das neue Leuchtenprofil wird in der App dargestellt

4. Erneut auf das Modul klicken und „Nutzen in Ihr Netzwerkname“ wählen.
5. Anschließend kann die Leuchte unter dem Punkt „Leuchten“ bedient werden.
6. Grundlegende Gesten in der App :
 - a. Auf die Abbildung einer Leuchte klicken um sie ein- oder auszuschalten.
 - b. Auf die Abbildung einer Leuchte klicken und nach rechts oder links bewegen um die Lichtstärke der Leuchte einzustellen.
 - c. Auf die Abbildung einer Leuchte klicken und nach oben oder unten bewegen um die Farbtemperatur der Leuchte anzupassen.
7. Eine detaillierte Bedienungsanleitung der App finden Sie unter der Homepage www.regiolux.de > Light Control > FLEX > FLEX10L > Zubehör

EN

1. Download “Casambi” app on the mobile device
2. Create a Network
 - a. A network must be named (e.g., Office1) and can be password protected.
 - b. To set a password, an internet access is required. Also an e-mail address and a user and administration password are necessary.
3. Change / select profile in the app

Necessary operation before adding to a network.

| <u>Abbreviation</u> | <u>Description</u> |
|--|---|
| BC | Broadcast (all devices together) |
| A0,A1,A2,... | DALI single address (=single devices) |
| G0,G1,G2, ... | DALI group address (= group of devices) |
| Recommended profile for Standard-DALI-luminaires (DT6) | bDW (1pB – DALI/BC/Dim) |
| Recommended profile for Tunable-White-luminaires(DT8) | bDW (1pB - DT8/BC/Dim,TW) |

Procedure to change a profile :

- Click on "More" at the bottom right.
- Then click on "Nearby devices" (All available modules are listed here).
- Select module and click on "Change profile".
- Select suitable profile. (See table for recommendation)
- Start update.

The new luminaire profile is displayed in the app

4. Click on the module again and select "Use in your network name"
5. Afterwards, the luminaire can be operated under the "Luminaires" item.
6. Basic gestures in the App :
 - a. Tap the image of a luminaire to turn it on or off.
 - b. Tap the image and move your finger to the right or left to control the luminaire intensity.
 - c. Tap the image and move your finger up or down to control the color temperature of the luminaire.
7. You can find detailed operating instructions for the app at www.regiolux.de > Light Control > FLEX > FLEX10L > Accessories.