

VARDIFLEX IP67 24 V

The VARDIFLEX IP67 24 V LED board is suitable for installation in dry and in wet rooms.



Risk of electric shock!

Be sure to have a professional electrician complete installation. There is no warranty coverage for any lights installed without observing European safety directives.



Caution!

Only connect the LED board to a suitable power supply 24 V DC.

Only operate when completely unrolled.


Connect LED boards in parallel.

Delivery includes

VARDIFLEX IP67 24 V

- 1 x 5 metre LED board
- 1 x male connector
- 1 x end cap
- 10 x mounting clip

Technical data

Power supply	24 V power supply with constant output voltage.
Power	24 W
Current strength	1 A
Radiation angle	120°
Quantity LED	300
Length	Maximum 10 metres per connection.
Dimensions	5000 x 8 x 3 mm
Bending radius	20 mm
	Safety class 3 - low voltage protection



Compliant with the applicable European CE directives.

Installation



Risk of electric shock!

Switch off voltage prior to installation. Ensure that voltage cannot be accidentally switched on again.

Mounting VARDIFLEX IP67 24 V



Caution!

On conducting surfaces, place an insulation layer between the LED board and surface. Surfaces must be flat, free of dust, grease and dry.

1. Prepare surface.
2. Shorten LED board if necessary.
3. Only use item 86993 exclusively to seal the shortened part of the LED board.
4. Peel off adhesive film and gently press on LED board, do not press directly on the LEDs.
5. Connect LED board to power supply.



Caution!

With soldered connections note that the soldering temperature is 260° C and the soldering duration a maximum of 10 seconds per soldering point.



Caution!

Only use neutral cross-linked silicon (never use silicon which includes vinegar!).



Disposal

Dispose of electrical and electronic equipment in an environmentally friendly manner. Please contact your local council for further information.

