
## LED-Dimmer 24 V DC, DALI-, 1-10 V-, PUSH-DIM dimmbar Article no. 17502000









## Tender

LED-Dimmer 24 V DC, DALI-, 1-10 V-, PUSH-DIM dimmbar, white.Single-channel (one-color) LED dimmer for constant voltage operation (24 V DC). Wiring is carried out using plug terminals. Cable cross section: 0.5 - 2.5 mm<sup>2</sup>. An external power supply is required for operation. Output signal (dimming): PWM (pulse width modulation). With protection against overload, short-circuit, overtemperature and idle run, maximum output current: 5 A. The device can be controlled using DALI or a push-button (Push-dim) or 1-10 V. In order to increase the power, multiple devices can be operated as master / slave. Material: Plastic, Degree of protection: according to DIN EN 60529 IP20, Protection class: (EN 61140) III, Voltage: 24V DC, Power: 120 W, Control: DALI.

Article data	
Article no.	17502000
GTIN	4250047782070
Short description	LED-Dimmer 24 V DC, DALI-, 1-10 V-, PUSH-DIM dimmbar
Material	Plastic
Colour	White
Length	183 mm
Width	33 mm
Hight	23 mm
Weight	0.083 kg
stamp	ENEC 22
Conformance	CE, UKCA

All technical data as well as, weight and measurements are based on rated values and had been carefully prepared. We reserve the right to make technical changes which are are important in progressing. Product pictures are examples and can vary from the original. Subject to errors. Date 06.06.2025 Orders are placed under our general terms and conditions under https://www.brumberg.com/en/terms-and-conditions/general-terms-and-conditions-of-sale/

Operating technology of driver



## **LED-Dimmer 24 V DC, DALI-, 1-10 V-, PUSH-DIM dimmbar** Article no. 17502000

Operating technology of driver	
Protection class	
Degree of protection	IP20
Power min	1 W
Power max.	120 W
Output voltage max	24.00 V
Control	DALI, 1-10 V, PUSH-Dimm
Enviroment temprature (ta)	-20 °C bis +40 °C
Measure point (tc)	max. +55 °C
Packing data	
Gross weight	0.109 kg
Length of packaging	45 mm
Packaging width	35 mm
Packaging hight	190 mm
	This product must not be disposed of with household waste. You are obliged, to dispose of
	such electrical waste separately.
Disposal at end of life	By disposing of electrical waste and other old or defective electronics separately, you
	support recycling or other forms of re-use. In that way you help to take care and to avoid that
	harmful substances get into the environment.