BRUMBERG

MINERVA MINI Surface mounted luminaire, IP43

Article no. 58293000

Light. For Generations.





Tender

Surface mounted luminaire, IP43, opal, Round. Surface mounting, Ceiling-/Wall-mounted Ceiling or wall surface mounted luminaire designed as a glass lamp. In timeless, round design in E27 version. Hand-blown opal glass with glass fastening via bayonet closure. Mounting method: Surface mounting, Place of installation: Ceiling-/Wall-mounted, Degree of protection: according to DIN EN 60529 IP43, Protection class: (EN 61140) I, Voltage: 230V AC 50Hz, Power: 60 W, Amount of light sources / fittings: 1 Qty, Control: on/off.

| Article data | |
|-------------------|---------------------------------|
| Article no. | 58293000 |
| GTIN | 4251433921318 |
| Series name | MINERVA MINI |
| Short description | Surface mounted luminaire, IP43 |
| Material | Steel |
| Colour | White |
| Type of surface | Matt |
| Shape | Round |
| Outer diameter | 310 mm |
| Hight | 70 mm |
| Weight | 2.021 kg |

BRUMBERG

MINERVA MINI Surface mounted luminaire, IP43

Article no. 58293000

Light. For Generations.

| Operating technology of the luminaire | |
|---------------------------------------|-------------------|
| System output | 120 W |
| Voltage type | AC |
| AC nominal voltage max | 230 V |
| Frequenz max. | 50 Hz |
| Lamp | Incandescent lamp |
| Lamp holder | E27 |
| Protection class | |
| Degree of protection | IP43 |
| Control | Other |
| Bulb change possible | Yes |

| Mounting technology | |
|-----------------------|-----------------------|
| Mounting method | Surface mounting |
| Place of installation | Ceiling-/Wall-mounted |
| Adjustability | Not adjustable |

| Packing data | |
|-------------------------|--|
| Gross weight | 4.076 kg |
| Length of packaging | 400 mm |
| Packaging width | 400 mm |
| Packaging hight | 300 mm |
| | This product must not be disposed of with household waste. You are obliged, to dispose of such electrical waste separately. |
| Disposal at end of life | By disposing of electrical waste and other old or defective electronics separately, you support recycling or other forms of re-use. In that way you help to take care and to avoid that harmful substances get into the environment. |