

ZigBee LED radio remote control for 18157000
Artikel-Nr. 18207000



ZigBee LED radio controller for the ZigBee LED dimmer 18157000. Enables the coupling of ZigBee lighting devices through Touchlink commissioning. Supports search and binding mode for coupling with the ZigBee lighting devices. Enables binding and controlling of universal DIM-, CCT-, RGB-, RGBW- and RGB + CCT ZigBee lighting devices. Transmission range (visual contact): up to 30 m. Up to four groups (maximum 30 receivers) can be controlled independently using one remote control. Seven individual colors and brightness values can be saved and called. Six preset scenes and five color temperatures can be called. The RGB color saturation can be adjusted. Voltage (battery): 6 V DC - 2 x CR2032 (not included in the scope of delivery), Frequency: 2.4 GHz, transmission power (Ps) < 100 mW, protocol: ZigBee 3.0, (Dimensions: L 137 x W 45 x H 13 mm, material: plastic . Degree of protection: according to DIN EN 60529 IP20.

Artikel-Nr.	18207000
Stand:	06.12.2021 16:10

Material	Plastic
Degree of protection	IP20
Length	137 mm

Width	45 mm
Aufbauhöhe	13 mm